

X-MAP4P

Digital Multi-audio Player

Honeywell



- Two individual USB\SD\BT and AM\FM line output.
- Can play music in two zones at the same time. Mix audio RCA output as well.
- Volume of two line outputs can be adjusted respectively.
- Supports USB high speed、SD Cards, Bluetooth Protocol V4.2.
- Support FLA, WMA, APE, FLAC, WAV, ACC, SBC, MP3 formats.
- AM/FM broadcasting is acceptable, can each save up 60 channels.

Technical Specifications

Power supply	100-240V AC < 15W 50/60Hz
Input	AM/FM 75Ω antenna interface USB port, SD card slot, Bluetooth.
Output	Stereo sound RCA output FM/AM tuner (775mV) Stereo sound RCA output USB/SD/BT (775mV) Mix audio RCA output: 775mV
Channels	3
Unit size	482(W)×44(H)×236(D) mm
Carton size	520(W)×120(H)×368(D) mm
Frequency response(dB)	20-20KHz ±3dB
Audio distortion (1 KHz)	0.05%
S/N RATIO(A-WTD)	≥80
Wave band frequency range	FM : 87.0MHz ~ 108MHz, FM : 76.0MHz ~ 90MHz step:0.1MHz AM : 522KHz ~ 1620KHz step:9KHz, AM : 520KHz ~ 1620KHz step:10KHz

Honeywell Audiovisuals

No. 257 Junye Road,
Guangzhou GETDD East
510530, China

Tel: +86 (0)20 2839 9600

Fax: +86 (0)20 2820 8706

<http://www.honeywell.com>

X-MAP4P_EN1.0

July 2019

© 2019 Honeywell International Inc.

Honeywell